

Tab.1. Ricevitori Classici.

Apparato	PreAmp.	+ Filtro	Noise/Notch	Noise/Sig	NPR-DR	NF	MDS CW	note:
		fig.6	dBm/Hz	dBm/Hz	dB	dB	dBm	
CDC-2000 (IK4AUY)			-88	-164	76	10	-137	1

IC-775 DSP	No	No	-95	-164	69	10	-137	
IC-775 DSP	No	Si	-90	-162	72	12	-135	
IC-775 DSP	Si.	No	-101	-166	65	8	-139	2

FT-2000 (2009)	No		-90	-155	65	19	-128	
FT-2000 (2009)	No	Si	-81	-153	72	21	-126	
FT-2000 (2009)	No	VRF	-91	-158	67	16	-131	
FT-2000 (2009)	Si.		-100	-166	66	8	-139	3

TS-590	No		-96	-159	63	15	-132	
TS-590	No	Si	-81	-157	76	17	-130	
TS-590	Si.		-100	-166	66	8	-139	
TS-590	Si.	Si	-90	-165	75	9	-138	4

IC-7000	No		-93	-156	63	18	-129	
IC-7000	No	Si	-85	-152	67	22	-125	
IC-7000	Si.		-105	-165	60	9	-138	
IC-7000	Si.	Si	-95	-162	67	12	-135	5

Elecraft K3	No		-80	-146	66	28	-119	
Elecraft K3	No	Si	-71	-142	71	32	-115	
Elecraft K3	Si.		-87	-153	66	21	-126	6

FT-857D	No		-93	-157	64	17	-130	
FT-857D	No	Si	-84	-153	69	21	-126	
FT-857D	Si.		-106	-164	58	10	-137	
FT-857D	Si.	Si	-92	-161	69	13	-134	7

IC-706	No		-105	-154	49	20	-127	
IC-706	No	Si	-86	-151	65	23	-124	
IC-706	Si.		-115	-167	52	7	-140	
IC-706	Si.	Si	-101	-166	65	8	-139	8

Tab. 2. Ricevitori SDR.

Apparato	PreAmp.	+ Filtro	Noise/Notch	Noise/Sig	NPR-DR	NF	MDS CW	note:
		fig.6	dBm/Hz	dBm/Hz	dB	dB	dBm	
PMSDR	No	PassTr	-134	-160	26	14	-133	
PMSDR	No	12-30	-119	-159	40	15	-132	
PMSDR	No	Si	-94	-157	63	17	-130	9

Flex-1500	0		-87	-137	50	37	-110	
Flex-1500	0	Si	-82	-135	53	39	-108	

SoftRock 40m	No	No	-86	-154	68	20	-127	11
--------------	----	----	-----	------	----	----	------	----

Tab. 3. Ricevitore Perseus.

Apparato	Presele	PreAmp	Noise/Notch dBm/Hz	Noise/Sig dBm/Hz	NPR-DR dB	NF dB	MDS CW dBm	note:
Perseus	.	off	-91	-155	64	19	-128	12